

PNP SILICON POWER TRANSISTOR 2SB772

PNP SILICON POWER TRANSISTOR

DESCRIPTION

The 2SB772 is PNP silicon transistor suited for the output stage of 3 W audio amplifier, voltage regulator, DC-DC converter and relay driver.


FEATURES

- · Low saturation voltage
 - $V_{CE(sat)} \le -0.5 \text{ V (Ic} = -2 \text{ A, I}_B = -0.2 \text{ A)}$
- Excellent he linearity and high he he = 60 to 400 (Vce = -2 V, Ic = -1 A)
- Less cramping space required due to small and thin package and reducing the trouble for attachment to a radiator.
 No insulator bushing required.

ABSOLUTE MAXIMUM RATINGS

Maximum Temperature -55 to +150°C Storage Temperature Junction Temperature 150°C Maximum Maximum Power Dissipation Total Power Dissipation ($T_A = 25^{\circ}C$) 1.0 W Total Power Dissipation (Tc = 25°C) 10 W Maximum Voltages and Currents (T_A = 25°C) VcBo Collector to Base Voltage -40 V VCEO Collector to Emitter Voltage -30 V Emitter to Base Voltage VEBO -5.0 V Collector Current (DC) -3.0 AIC(DC) IC(pulse) Note Collector Current (pulse) -7.0 A

* PACKAGE DRAWING (Unit: mm)



- 1: Emitter
- 2: Collector: connected to mounting plane
- 3: Base

ELECTRICAL CHARACTERISTICS (TA = 25°C)

Note Pulse Test PW \leq 350 μ s, Duty Cycle \leq 2%

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
DC Current Gain	h _{FE1}	$V_{CE} = -2.0 \text{ V}, I_{C} = -20 \text{ mA}^{Note}$	30	220		
DC Current Gain	h _{FE2}	$V_{CE} = -2.0 \text{ V, I}_{C} = -1.0 \text{ mA}^{Note}$	60	160	400	
Gain Bandwidth Product	f⊤	$V_{CE} = -5.0 \text{ V}, I_{C} = -0.1 \text{ A}$		80		MHz
Output Capacitance	Cob	V _{CB} = -10 V, I _E = 0, f = 1.0 MHz		55		pF
Collector Cutoff Current	Ісво	V _{CB} = -30 V, I _E = 0 A			-1.0	μΑ
Emitter Cutoff Current	Ієво	$V_{EB} = -3.0 \text{ V}, \text{ Ic} = 0 \text{ A}$			-1.0	μΑ
Collector Saturation Voltage	V _{CE(sat)}	$I_C = -2.0 \text{ A}, I_B = -0.2 \text{ A}^{\text{Note}}$		-0.3	-0.5	V
Base Saturation Voltage	V _{BE(sat)}	$I_C = -2.0 \text{ A}, I_B = -0.2 \text{ A}^{\text{Note}}$		-1.0	-2.0	V

Note Pulse Test: PW \leq 350 μ s, Duty Cycle \leq 2%


CLASSIFICATION OF hee


Rank	R	Q	Р	E
Range	60 to 120	100 to 200	160 to 320	200 to 400


Remark Test Conditions: $V_{CE} = -2.0 \text{ V}$, $I_{C} = 1.0 \text{ A}$


The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version. Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.


TYPICAL CHARACTERISTICS (T_A = 25°C, unless otherwise noted.)























- The information in this document is current as of March, 2004. The information is subject to change
 without notice. For actual design-in, refer to the latest publications of NEC Electronics data sheets or
 data books, etc., for the most up-to-date specifications of NEC Electronics products. Not all
 products and/or types are available in every country. Please check with an NEC Electronics sales
 representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without the prior
 written consent of NEC Electronics. NEC Electronics assumes no responsibility for any errors that may
 appear in this document.
- NEC Electronics does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC Electronics products listed in this document or any other liability arising from the use of such products. No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Electronics or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative
 purposes in semiconductor product operation and application examples. The incorporation of these
 circuits, software and information in the design of a customer's equipment shall be done under the full
 responsibility of the customer. NEC Electronics assumes no responsibility for any losses incurred by
 customers or third parties arising from the use of these circuits, software and information.
- While NEC Electronics endeavors to enhance the quality, reliability and safety of NEC Electronics products, customers agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects in NEC Electronics products, customers must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.
- NEC Electronics products are classified into the following three quality grades: "Standard", "Special" and
 "Specific".
 - The "Specific" quality grade applies only to NEC Electronics products developed based on a customer-designated "quality assurance program" for a specific application. The recommended applications of an NEC Electronics product depend on its quality grade, as indicated below. Customers must check the quality grade of each NEC Electronics product before using it in a particular application.
 - "Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots.
 - "Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support).
 - "Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC Electronics products is "Standard" unless otherwise expressly specified in NEC Electronics data sheets or data books, etc. If customers wish to use NEC Electronics products in applications not intended by NEC Electronics, they must contact an NEC Electronics sales representative in advance to determine NEC Electronics' willingness to support a given application.

(Note)

- (1) "NEC Electronics" as used in this statement means NEC Electronics Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC Electronics products" means any product developed or manufactured by or for NEC Electronics (as defined above).