

## ±15kV ESD Protected, +3V to +5.5V, 1μA, 250kbps, RS-232 Transmitters/Receivers

### ICL3221E, ICL3222E, ICL3223E, ICL3232E, ICL3241E, ICL3243E

The Intersil ICL32xxE devices are 3.0V to 5.5V powered RS-232 transmitters/receivers which meet EIA/TIA-232 and V.28/V.24 specifications, even at  $V_{CC}$  = 3.0V. Additionally, they provide ±15kV ESD protection (IEC61000-4-2 Air Gap and Human Body Model) on transmitter outputs and receiver inputs (RS-232 pins). Targeted applications are PDAs, Palmtops, and notebook and laptop computers where the low operational, and even lower standby, power consumption is critical. Efficient on-chip charge pumps, coupled with manual and automatic power-down functions (except for the ICL3232E), reduce the standby supply current to a 1µA trickle. Small footprint packaging, and the use of small, low value capacitors ensure board space savings as well. Data rates greater than 250kbps are guaranteed at worst case load conditions. This family is fully compatible with 3.3V-only systems, mixed 3.3V and 5.0V systems, and 5.0V-only systems.

The ICL324XE are 3-driver, 5-receiver devices that provide a complete serial port suitable for laptop or notebook computers. Both devices also include noninverting always-active receivers for "wake-up" capability.

The ICL3221E, ICL3223E and ICL3243E, feature an *automatic power-down* function which powers down the on-chip power-supply and driver circuits. This occurs when an attached peripheral device is shut off or the RS-232 cable is removed, conserving system power automatically without changes to the hardware or operating system. These devices power up again when a valid RS-232 voltage is applied to any receiver input.

Table 1 summarizes the features of the devices represented by this data sheet, while Application Note <u>AN9863</u> summarizes the features of each device comprising the ICL32xxE 3V family.

### **Features**

- ESD Protection for RS-232 I/O Pins to ±15kV (IEC61000)
- Drop in Replacements for MAX3221E, MAX3222E, MAX3223E, MAX3232E, MAX3241E, MAX3243E, SP3243E
- ICL3221E is a Low Power, Pin Compatible Upgrade for 5V MAX221E
- ICL3222E is a Low Power, Pin Compatible Upgrade for 5V MAX242E, and SP312E
- ICL3232E is a Low Power Upgrade for HIN232E, ICL232 and Pin Compatible Competitor Devices
- RS-232 Compatible with  $V_{CC} = 2.7V$
- Meets EIA/TIA-232 and V.28/V.24 Specifications at 3V
- Latch-Up Free
- On-Chip Voltage Converters Require Only Four External 0.1µF Capacitors
- Manual and Automatic Power-Down Features
- Guaranteed Mouse Driveability (ICL324xE Only)
- Receiver Hysteresis For Improved Noise Immunity
- Guaranteed Minimum Data Rate. . . . . . . 250kbps
- Wide Power Supply Range . . . . Single +3V to +5.5V
- Low Supply Current in Power-Down State . . . . 1µA
- Pb-Free Available (RoHS Compliant)

### **Applications**

- Any System Requiring RS-232 Communication Ports
  - Battery Powered, Hand-Held, and Portable Equipment
  - Laptop Computers, Notebooks, Palmtops
  - Modems, Printers and other Peripherals
  - Digital Cameras
  - Cellular/Mobile Phones

### **Related Literature**

 Technical Brief <u>TB363</u> "Guidelines for Handling and Processing Moisture Sensitive Surface Mount Devices (SMDs)"

1

PART NUMBER	NUMBER OF Tx	NUMBER OF Rx	NUMBER OF MONITOR RECEIVERS (R <sub>OUTB</sub> )	DATA RATE (kbps)	RECEIVER ENABLE FUNCTION?	READY OUTPUT?	MANUAL POWER-DOWN?	AUTOMATIC POWER- DOWN FUNCTION?
ICL3221E	1	1	0	250	Yes	No	Yes	Yes
ICL3222E	2	2	0	250	Yes	No	Yes	No
ICL3223E	2	2	0	250	Yes	No	Yes	Yes
ICL3232E	2	2	0	250	No	No	No	No
ICL3241E	3	5	2	250	Yes	No	Yes	No
ICL3243E	3	5	1	250	No	No	Yes	Yes

#### TABLE 1. SUMMARY OF FEATURES

### **Typical Operating Circuits**



NOTE: THE NEGATIVE TERMINAL OF  $\mathsf{C}_3$  CAN BE CONNECTED TO EITHER  $\mathsf{V}_{\mathsf{CC}}$  OR GND

### Typical Operating Circuits (Continued)



NOTE: THE NEGATIVE TERMINAL OF C3 CAN BE CONNECTED TO EITHER V<sub>CC</sub> OR GND



#### ICL3232E -) - C3 (OPTIONAL CONNECTION, NOTE) +3.3V 0.1µF 16 NOTE: THE NEGATIVE TERMINAL OF $\rm C_3$ CAN BE CONNECTED TO EITHER V\_{CC} OR GND \_\_\_\_+ C3 \_\_\_\_\_ 0.1μF \_\_\_\_\_\_ 1 С<sub>1</sub> C1+ 2 v<sub>cc</sub> L+ V+ 0.1µF 3 C1-4 C<sub>2</sub> C2+ 6 \_\_\_\_\_ \_\_\_\_\_\_\_\_\_\_\_ 0.1µF V-5 C2-T1 11 14 T1<sub>IN</sub> T1<sub>OUT</sub> T<sub>2</sub> 7 10 T2<sub>IN</sub> ►T2<sub>OUT</sub> TTL/CMOS RS-232 LOGIC LEVELS R1<sub>OUT</sub> <mark>↓</mark>12 13 LEVELS R1<sub>IN</sub> ₹₅ĸΩ R<sub>1</sub> 8 9 R2<sub>OUT</sub> R2<sub>IN</sub> 4 $R_2$ ₹5kΩ -GND 15 ᆂ

### Typical Operating Circuits (Continued)



### Typical Operating Circuits (Continued)

### **Pin Configurations**













ICL3222E

ICL323 (16 LD SOIC, SSO TOP VII	P, TSSOP-16)
C1+ 1	16 VCC
V+ 2	15 GND
C1- 3	14 T10UT
C2+ 4	13 R1IN
C2- 5	12 R10UT
V- 6	11 T1IN
T2OUT 7	10 T2IN
R2IN 8	9 R2OUT

### Pin Configurations (Continued)

ICL3241 (28 LD SOIC, SSC		ICL3243E (28 LD SOIC, SSOP, 1	(SSOP)
TOP VIEV		TOP VIEW	
C2+ 1	28 C1+	C2+ 1	28 C1+
C2- 2	27 V+	C2- 2	27 V+
V- 3	26 VCC	V- 3	26 VCC
R1IN 4	25 GND	R1IN 4	25 GND
R2IN 5	24 C1-	R2IN 5	24 C1-
R3IN 6	23 EN	R3IN 6	23 FORCEON
R4IN 7	22 SHDN	R4IN 7	22 FORCEOFF
R5IN 8	21 R1OUTB	R5IN 8	21 INVALID
T1OUT 9	20 R2OUTB	T1OUT 9	20 R2OUTB
T2OUT 10	19 R1OUT	T2OUT 10	19 R1OUT
T3OUT 11	18 R2OUT	T3OUT 11	18 R2OUT
T3IN 12	17 R3OUT	T3IN 12	17 R3OUT
T2IN 13	16 R4OUT	T2IN 13	16 R4OUT
T1IN 14	15 R5OUT	T1IN 14	15 R5OUT

### **Pin Descriptions**

PIN	FUNCTION
VCC	System power supply input (3.0V to 5.5V).
V+	Internally generated positive transmitter supply (+5.5V).
V-	Internally generated negative transmitter supply (-5.5V).
GND	Ground connection.
C1+	External capacitor (voltage doubler) is connected to this lead.
C1-	External capacitor (voltage doubler) is connected to this lead.
C2+	External capacitor (voltage inverter) is connected to this lead.
C2-	External capacitor (voltage inverter) is connected to this lead.
TIN	TTL/CMOS compatible transmitter Inputs.
TOUT	$\pm$ 15kV ESD Protected, RS-232 level (nominally $\pm$ 5.5V) transmitter outputs.
RIN	±15kV ESD Protected, RS-232 compatible receiver inputs.
ROUT	TTL/CMOS level receiver outputs.
ROUTB	TTL/CMOS level, noninverting, always enabled receiver outputs.
INVALID	Active low output that indicates if no valid RS-232 levels are present on any receiver input.
EN	Active low receiver enable control; doesn't disable R <sub>OUTB</sub> outputs.
SHDN	Active low input to shut down transmitters and on-board power supply, to place device in low power mode.
FORCEOFF	Active low to shut down transmitters and on-chip power supply. This overrides any automatic circuitry and FORCEON (see Table 2).
FORCEON	Active high input to override automatic power-down circuitry thereby keeping transmitters active ( $\overline{\text{FORCEOFF}}$ must be high).

### **Ordering Information**

PART NUMBER (Note 3)	PART MARKING	TEMP RANGE (°C)	PACKAGE	РКG. DWG. # M16.209	
ICL3221ECA	ICL 3221ECA	0 to +70	16 Ld SSOP		
ICL3221ECA-T (Note 1)	ICL 3221ECA	0 to +70	16 Ld SSOP	M16.209	
ICL3221ECAZ (Note 2)	ICL32 21ECAZ	0 to +70	16 Ld SSOP (Pb-free)	M16.209	
ICL3221ECAZ-T (Notes 1, 2)	ICL32 21ECAZ	0 to +70	16 Ld SSOP (Pb-free)	M16.209	
ICL3221ECAZA (Note 2)	ICL32 21ECAZ	0 to +70	16 Ld SSOP (Pb-free)	M16.209	
ICL3221ECAZA-T (Notes 1, 2)	ICL32 21ECAZ	0 to +70	16 Ld SSOP (Pb-free)	M16.209	
ICL3221ECV	3221 ECV	0 to +70	16 Ld TSSOP	M16.173	
ICL3221ECVZ (Note 2)	3221 ECVZ	0 to +70	16 Ld TSSOP (Pb-free)	M16.173	
ICL3221ECVZ-T (Notes 1, 2)	3221 ECVZ	0 to +70	16 Ld TSSOP (Pb-free)	M16.173	
ICL3221EIA	ICL 3221EIA	-40 to +85	16 Ld SSOP	M16.209	
ICL3221EIA-T (Note 1)	ICL 3221EIA	-40 to +85	16 Ld SSOP	M16.209	
ICL3221EIAZ (Note 2)	ICL32 21EIAZ	-40 to +85	16 Ld SSOP (Pb-free)	M16.209	
ICL3221EIAZ-T (Notes 1, 2)	ICL32 21EIAZ	-40 to +85	16 Ld SSOP (Pb-free)	M16.209	
ICL3221EIVZ (Note 2)	3221 EIVZ	-40 to +85	16 Ld TSSOP (Pb-free)	M16.173	
ICL3221EIVZ-T (Notes 1, 2)	3221 EIVZ	-40 to +85	16 Ld TSSOP (Pb-free)	M16.173	
ICL3222ECA-T (Note 1)	ICL 3222ECA	0 to +70	20 Ld SSOP	M20.209	
ICL3222ECAZ (Note 2)	ICL32 22ECAZ	0 to +70	20 Ld SSOP (Pb-free)	M20.209	
ICL3222ECAZ-T (Notes 1, 2)	ICL32 22ECAZ	0 to +70	20 Ld SSOP (Pb-free)	M20.209	
ICL3222ECP	ICL3222ECP	0 to +70	18 Ld PDIP	E18.3	
ICL3222ECV-T (Note 1)	ICL 3222ECV	0 to +70	20 Ld TSSOP	M20.173	
ICL3222ECVZ (Note 2)	ICL32 22ECVZ	0 to +70	20 Ld TSSOP (Pb-free)	M20.173	
ICL3222ECVZ-T (Notes 1, 2)	ICL32 22ECVZ	0 to +70	20 Ld TSSOP (Pb-free)	M20.173	
ICL3222EIAZ (Note 2)	ICL32 22EIAZ	-40 to +85	20 Ld SSOP (Pb-free)	M20.209	
ICL3222EIAZ-T (Notes 1, 2)	ICL32 22EIAZ	-40 to +85	20 Ld SSOP (Pb-free)	M20.209	
ICL3222EIB	ICL3222EIB	-40 to +85	18 Ld SOIC	M18.3	
ICL3222EIB-T (Note 1)	ICL3222EIB	-40 to +85	18 Ld SOIC	M18.3	
ICL3222EIBZ (Note 2)	3222EIBZ	-40 to +85	18 Ld SOIC (Pb-free)	M18.3	
ICL3222EIBZ-T (Notes 1, 2)	3222EIBZ	-40 to +85	18 Ld SOIC (Pb-free)	M18.3	
ICL3222EIV	ICL 3222EIV	-40 to +85	20 Ld TSSOP	M20.173	
ICL3222EIV-T (Note 1)	ICL 3222EIV	-40 to +85	20 Ld TSSOP	M20.173	
ICL3222EIVZ (Note 2)	ICL32 22EIVZ	-40 to +85	20 Ld TSSOP (Pb-free)	M20.173	
ICL3222EIVZ-T (Notes 1, 2)	ICL32 22EIVZ	-40 to +85	20 Ld TSSOP (Pb-free)	M20.173	
ICL3223ECA	ICL 3223ECA	0 to +70	20 Ld SSOP	M20.209	
ICL3223ECA-T (Note 1)	ICL 3223ECA	0 to +70	20 Ld SSOP	M20.209	
ICL3223ECAZ (Note 2)	ICL32 23ECAZ	0 to +70	20 Ld SSOP (Pb-free)	M20.209	
ICL3223ECAZ-T (Notes 1, 2)	ICL32 23ECAZ	0 to +70	20 Ld SSOP (Pb-free)	M20.209	
ICL3223ECV	ICL 3223ECV	0 to +70	20 Ld TSSOP	M20.173	
ICL3223ECVZ (Note 2)	ICL32 23ECVZ	0 to +70	20 Ld TSSOP (Pb-free)	M20.173	
ICL3223ECVZ-T (Notes 1, 2)	ICL32 23ECVZ	0 to +70	20 Ld TSSOP (Pb-free)	M20.173	

### Ordering Information (Continued)

PART NUMBER (Note 3)	PART MARKING	TEMP RANGE (°C)	PACKAGE	PKG. DWG. #	
ICL3223EIA	ICL 3223EIA	-40 to +85	20 Ld SSOP	M20.209	
ICL3223EIA-T (Note 1)	ICL 3223EIA	-40 to +85	20 Ld SSOP	M20.209	
ICL3223EIAZ (Note 2)	ICL32 23EIAZ	-40 to +85	20 Ld SSOP (Pb-free)	M20.209	
ICL3223EIAZ-T (Notes 1, 2)	ICL32 23EIAZ	-40 to +85	20 Ld SSOP (Pb-free)	M20.209	
ICL3223EIV	ICL 3223EIV	-40 to +85	20 Ld TSSOP	M20.173	
ICL3223EIVZ (Note 2)	ICL32 23EIVZ	-40 to +85	20 Ld TSSOP (Pb-free)	M20.173	
ICL3223EIVZ-T (Notes 1, 2)	ICL32 23EIVZ	-40 to +85	20 Ld TSSOP (Pb-free)	M20.173	
ICL3232ECA	ICL 3232ECA	0 to +70	16 Ld SSOP	M16.209	
ICL3232ECA-T (Note 1)	ICL 3232ECA	0 to +70	16 Ld SSOP	M16.209	
ICL3232ECAZ (Note 2)	3232 ECAZ	0 to +70	16 Ld SSOP (Pb-free)	M16.209	
ICL3232ECAZ-T (Notes 1, 2)	3232 ECAZ	0 to +70	16 Ld SSOP (Pb-free)	M16.209	
ICL3232ECBZ (Note 2)	3232ECBZ	0 to +70	16 Ld SOIC (Pb-free)	M16.3	
ICL3232ECBZ-T (Notes 1, 2)	3232ECBZ	0 to +70	16 Ld SOIC (Pb-free)	M16.3	
ICL3232ECBN	3232ECBN	0 to +70	16 Ld SOIC	M16.15	
ICL3232ECBN-T (Note 1)	3232ECBN	0 to +70	16 Ld SOIC	M16.15	
ICL3232ECBNZ (Note 2)	3232ECBNZ	0 to +70	16 Ld SOIC (Pb-free)	M16.15	
ICL3232ECBNZ-T (Notes 1, 2)	3232ECBNZ	0 to +70	16 Ld SOIC (Pb-free)	M16.15	
ICL3232ECV-16T (Note 1)	3232E CV-16	0 to +70	16 Ld TSSOP	M16.173	
ICL3232ECV-16Z (Note 2)	3232E CV-16Z	0 to +70	16 Ld TSSOP (Pb-free)	M16.173	
ICL3232ECV-16Z-T (Notes 1, 2)	3232E CV-16Z	0 to +70	16 Ld TSSOP (Pb-free)	M16.173	
ICL3232ECV-20Z (Note 2)	ICL3232 ECV-20Z	0 to +70	20 Ld TSSOP (Pb-free)	M20.173	
ICL3232ECV-20Z-T (Notes 1, 2)	ICL3232 ECV-20Z	0 to +70	20 Ld TSSOP (Pb-free)	M20.173	
ICL3232EFV-16Z (Note 2)	3232E FV-16Z	-40 to +125	16 Ld TSSOP (Pb-free)	M16.173	
ICL3232EFV-16Z-T (Notes 1, 2)	3232E FV-16Z	-40 to +125	16 Ld TSSOP (Pb-free)	M16.173	
ICL3232EIA-T (Note 1)	ICL3232 EIA	-40 to +85	16 Ld SSOP	M16.209	
ICL3232EIAZ (Note 2)	3232 EIAZ	-40 to +85	16 Ld SSOP (Pb-free)	M16.209	
ICL3232EIAZ-T (Notes 1, 2)	3232 EIAZ	-40 to +85	16 Ld SSOP (Pb-free)	M16.209	
ICL3232EIB-T (Note 1)	ICL3232EIB	-40 to +85	16 Ld SOIC	M16.3	
ICL3232EIBZ (Note 2)	3232EIBZ	-40 to +85	16 Ld SOIC (Pb-free)	M16.3	
ICL3232EIBZ-T (Notes 1, 2)	3232EIBZ	-40 to +85	16 Ld SOIC (Pb-free)	M16.3	
ICL3232EIBNZ (Note 2)	3232EIBNZ	-40 to +85	16 Ld SOIC (Pb-free)	M16.15	
ICL3232EIBNZ-T (Notes 1, 2)	3232EIBNZ	-40 to +85	16 Ld SOIC (Pb-free)	M16.15	
ICL3232EIV-16	3232E IV-16	-40 to +85	16 Ld TSSOP	M16.173	
ICL3232EIV-16-T (Note 1)	3232E IV-16	-40 to +85	16 Ld TSSOP	M16.173	
ICL3232EIV-16Z (Note 2)	3232E IV-16Z	-40 to +85	16 Ld TSSOP (Pb-free)	M16.173	
ICL3232EIV-16Z-T (Notes 1, 2)	3232E IV-16Z	-40 to +85	16 Ld TSSOP (Pb-free)	M16.173	
ICL3232EIV-20Z (Note 2)	ICL3232 EIV-20Z	-40 to +85	20 Ld TSSOP (Pb-free)	M20.173	
ICL3232EIV-20Z-T (Notes 1, 2)	ICL3232 EIV-20Z	-40 to +85	20 Ld TSSOP (Pb-free)	M20.173	
ICL3241ECA	ICL 3241ECA	0 to +70	28 Ld SSOP	M28.209	

9

### Ordering Information (Continued)

PART NUMBER (Note 3)	PART MARKING	TEMP RANGE (°C)	PACKAGE	PKG. DWG. #	
ICL3241ECA-T (Note 1)	ICL 3241ECA	0 to +70	28 Ld SSOP	M28.209	
ICL3241ECAZ (Note 2)	ICL3241 ECAZ	0 to +70	28 Ld SSOP (Pb-free)	M28.209	
ICL3241ECAZ-T (Notes 1, 2)	ICL3241 ECAZ	0 to +70	28 Ld SSOP (Pb-free)	M28.209	
ICL3241ECBZ (Note 2)	ICL3241ECBZ	0 to +70	28 Ld SOIC (Pb-free)	M28.3	
ICL3241ECBZ-T (Notes 1, 2)	ICL3241ECBZ	0 to +70	28 Ld SOIC (Pb-free)	M28.3	
ICL3241ECVZ (Note 2)	ICL3241 ECVZ	0 to +70	28 Ld TSSOP (Pb-free)	M28.173	
ICL3241EIA-T (Note 1)	ICL 3241EIA	-40 to +85	28 Ld SSOP	M28.209	
ICL3241EIAZ (Note 2)	ICL3241 EIAZ	-40 to +85	28 Ld SSOP (Pb-free)	M28.209	
ICL3241EIAZ-T (Notes 1, 2)	ICL3241 EIAZ	-40 to +85	28 Ld SSOP (Pb-free)	M28.209	
ICL3241EIBZ (Note 2)	ICL3241EIBZ	-40 to +85	28 Ld SOIC (Pb-free)	M28.3	
ICL3241EIBZ-T (Notes 1, 2)	ICL3241EIBZ	-40 to +85	28 Ld SOIC (Pb-free)	M28.3	
ICL3241EIV-T (Note 1)	ICL3241 EIV	-40 to +85	28 Ld TSSOP	M28.173	
ICL3241EIVZ (Note 2)	ICL3241 EIVZ	-40 to +85	28 Ld TSSOP (Pb-free)	M28.173	
ICL3241EIVZ-T (Notes 1, 2)	ICL3241 EIVZ	-40 to +85	28 Ld TSSOP (Pb-free)	M28.173	
ICL3243ECA	ICL 3243ECA	0 to +70	28 Ld SSOP	M28.209	
ICL3243ECA-T (Note 1)	ICL 3243ECA	0 to +70	28 Ld SSOP	M28.209	
ICL3243ECAZ (Note 2)	ICL32 43ECAZ	0 to +70	28 Ld SSOP (Pb-free)	M28.209	
ICL3243ECAZ-T (Notes 1, 2)	ICL32 43ECAZ	0 to +70	28 Ld SSOP (Pb-free)	M28.209	
ICL3243ECBZ (Note 2)	ICL3243ECBZ	0 to +70	28 Ld SOIC (Pb-free)	M28.3	
ICL3243ECBZ-T (Notes 1, 2)	ICL3243ECBZ	0 to +70	28 Ld SOIC (Pb-free)	M28.3	
ICL3243ECV-T (Note 1)	ICL3243 ECV	0 to +70	28 Ld TSSOP	M28.173	
ICL3243ECVZ (Note 2)	ICL3243 ECVZ	0 to +70	28 Ld TSSOP (Pb-free)	M28.173	
ICL3243ECVZ-T (Notes 1, 2)	ICL3243 ECVZ	0 to +70	28 Ld TSSOP (Pb-free)	M28.173	
ICL3243EIA-T (Note 1)	ICL 3243EIA	-40 to +85	28 Ld SSOP	M28.209	
ICL3243EIAZ (Note 2)	ICL32 43EIAZ	-40 to +85	28 Ld SSOP (Pb-free)	M28.209	
ICL3243EIAZ-T (Notes 1, 2)	ICL32 43EIAZ	-40 to +85	28 Ld SSOP (Pb-free)	M28.209	
ICL3243EIV	ICL3243 EIV	-40 to +85	28 Ld TSSOP	M28.173	
ICL3243EIVZ (Note 2)	ICL3243 EIVZ	-40 to +85	28 Ld TSSOP (Pb-free)	M28.173	
ICL3243EIVZ-T (Notes 1, 2)	ICL3243 EIVZ	-40 to +85	28 Ld TSSOP (Pb-free)	M28.173	

NOTES:

1. Please refer to  $\underline{\mathsf{TB347}}$  for details on reel specifications.

2. These Intersil Pb-free plastic packaged products employ special Pb-free material sets, molding compounds/die attach materials, and 100% matte tin plate plus anneal (e3 termination finish, which is RoHS compliant and compatible with both SnPb and Pb-free soldering operations). Intersil Pb-free products are MSL classified at Pb-free peak reflow temperatures that meet or exceed the Pb-free requirements of IPC/JEDEC J STD-020.

3. For Moisture Sensitivity Level (MSL), please see device information page for ICL3221E, ICL3222E, ICL3223E, ICL3223E, ICL3224E, ICL3243E. For more information on MSL please see techbrief <u>TB363</u>.

## Table of Contents

Related Literature 1
Typical Operating Circuits
Pin Configurations
Pin Descriptions7
Ordering Information
Absolute Maximum Ratings 12
Thermal Information 12
Recommended Operating Conditions
Electrical Specifications 12
Detailed Description14Charge-Pump14Transmitters14Receivers14
Low Power Operation
Pin Compatible Replacements for 5V Devices 15
Power-Down Functionality (Except ICL3232E)15Software Controlled (Manual) Power-Down15Automatic Power-Down (ICL3221E, ICL3223E, ICL3243E Only)17Receiver ENABLE Control (ICL3221E, ICL3222E, ICL3223E, ICL3241E Only)18
Capacitor Selection
Power Supply Decoupling 18
Operation Down to 2.7V 18
Transmitter Outputs when Exiting Power-Down 18
Mouse Driveability
High Data Rates
Interconnection with 3V and 5V Logic 19
±15kV ESD Protection 20   Human Body Model (HBM) Testing 20   IEC61000-4-2 Testing 20
Typical Performance Curves VCC = 3.3V, TA = +25°C
Die Characteristics
Revision History 22
Products
Package Outline Drawings

#### Absolute Maximum Ratings

V <sub>CC</sub> to GND -0.3V to 6V   V+ to GND -0.3V to 7V   V- to GND +0.3V to 7V   V+ to V- 14V
Input Voltages
T <sub>IN</sub> , FORCEOFF, FORCEON, EN, SHDN0.3V to 6V R <sub>IN</sub>
Output Voltages
$\begin{array}{cccc} T_{OUT} & & \pm 13.2V \\ R_{OUT}, & & INVALID \\ \end{array} \\ \begin{array}{c} T_{NVALID} & & INVALID \\ \end{array} \\ \begin{array}{c} V_{CC} & V_{CC} \\ V_{CC} & V_{CC} \end{array} \\ \end{array}$
Short Circuit Duration
T <sub>OUT</sub>

#### **Recommended Operating Conditions**

#### Temperature Range

ICL32xxECX 0°C to +70°C
ICL32xxEFX40°C to +125°C
ICL32xxEIX
Supply Voltage (V <sub>CC</sub> )
Rx Input Voltage15V to +15V

#### Thermal Information

Thermal Resistance (Typical, Note 4)	Θ <sub>JA</sub> (°C/W)
18 Ld PDIP Package*	80
16 Ld Wide SOIC Package	100
16 Ld Narrow SOIC Package	115
18 Ld SOIC Package	75
28 Ld SOIC Package	75
16 Ld SSOP Package	135
20 Ld SSOP Package	122
16 Ld TSSOP Package	145
20 Ld TSSOP Package	140
28 Ld SSOP and TSSOP Packages	100
Maximum Junction Temperature (Plastic Package)	. +150°C
Maximum Storage Temperature Range65°	C to +150°C
Pb-Free Reflow Profile	e link below
http://www.intersil.com/pbfree/Pb-FreeReflow.a	asp

CAUTION: Do not operate at or near the maximum ratings listed for extended periods of time. Exposure to such conditions may adversely impact product reliability and result in failures not covered by warranty.

#### NOTE:

4.  $\theta_{JA}$  is measured with the component mounted on a low effective thermal conductivity test board in free air. See Tech Brief TB379 for details.

#### **Electrical Specifications**

Test Conditions: V<sub>CC</sub> = 3V to 5.5V, C<sub>1</sub> - C<sub>4</sub> =  $0.1\mu$ F; Unless Otherwise Specified. Typicals are at T<sub>A</sub> = +25°C. **Boldface limits apply over the operating temperature range**.

PARAMETER	TEST CONDITIONS		TEMP (°C)	MIN (Note 6)	ТҮР	MAX (Note 6)	UNITS
DC CHARACTERISTICS							
Supply Current, Automatic Power-Down	All $R_{IN}$ Open, FORCEON = GND, FORCEOFF = $V_{CC}$ (ICL3221E, ICL3223E, ICL3243E Only)		25	-	1.0	10	μA
Supply Current, Power-Down	$\overline{\text{FORCEOFF}} = \overline{\text{SHDN}} = 0$	$\overline{\text{FORCEOFF}} = \overline{\text{SHDN}} = \text{GND} (\text{Except ICL3232E})$		-	1.0	10	μA
Supply Current, Automatic Power-Down	All Outputs Unloaded, FORCEON = FORCEOFF	V <sub>CC</sub> = 3.0V, ICL3241, ICL3243	25	-	0.3	1.0	mA
Disabled	= SHDN $=$ V <sub>CC</sub>	V <sub>CC</sub> = 3.0V, ICL3223	25	-	0.7	3.0	mA
		V <sub>CC</sub> = 3.15V, ICL3221, ICL3222, ICL3223, ICL3232	25	-	0.3	1.0	mA
LOGIC AND TRANSMITTE	ER INPUTS AND RECEI	VER OUTPUTS					
Input Logic Threshold Low	T <sub>IN</sub> , FORCEON, FORCEO	DFF, EN, SHDN	Full	-	-	0.8	V
Input Logic Threshold High		$V_{CC} = 3.3V$	Full	2.0	-	-	V
	FORCEOFF, EN, SHDN	$V_{CC} = 5.0V$	Full	2.4	-	-	V
Input Leakage Current	T <sub>IN</sub> , FORCEON,	All but ICL3232EF	Full	-	±0.01	±1.0	μA
	FORCEOFF, EN, SHDN	ICL3232EF	Full	-	±0.01	±10	μA
Output Leakage Current (Except ICL3232E)	$\overline{\text{FORCEOFF}}$ = GND or $\overline{\text{EN}}$ = V <sub>CC</sub>		Full	-	±0.05	±10	μA
Output Voltage Low	I <sub>OUT</sub> = 1.6mA		Full	-	-	0.4	V
Output Voltage High	$I_{OUT} = -1.0 mA$	All but ICL3232EF	Full	V <sub>CC</sub> - 0.6	V <sub>CC</sub> - 0.1	-	V
		ICL3232EF	Full	V <sub>CC</sub> - 0.9	V <sub>CC</sub> - 0.1	-	V

### ICL3221E, ICL3222E, ICL3223E, ICL3232E, ICL3241E, ICL3243E

**Electrical Specifications** Test Conditions:  $V_{CC} = 3V$  to 5.5V,  $C_1 - C_4 = 0.1\mu$ F; Unless Otherwise Specified. Typicals are at  $T_A = +25^{\circ}$ C. **Boldface limits apply over the operating temperature range.** (Continued)

PARAMETER	TEST CO	NDITIONS	TEMP (°C)	MIN (Note 6)	ТҮР	MAX (Note 6)	UNITS
AUTOMATIC POWER-DO	<b>NN</b> (ICL3221E, ICL3223	E, ICL3243E Only, FORCE	ON = G	ND, FORCEC	$\overline{FF} = V_{CC}$		
Receiver Input Thresholds to Enable Transmitters	ICL32xxE Powers Up (se	e Figure 6)	Full	-2.7	-	2.7	V
Receiver Input Thresholds to Disable Transmitters	ICL32xxE Powers Down	CL32xxE Powers Down (see Figure 6)			-	0.3	V
INVALID Output Voltage Low	I <sub>OUT</sub> = 1.6mA	<sub>DUT</sub> = 1.6mA			-	0.4	V
INVALID Output Voltage High	$I_{OUT} = -1.0 mA$	Full	V <sub>CC</sub> - 0.6	-	-	V	
Receiver Threshold to Transmitters Enabled Delay (t <sub>WU</sub> )			25	-	100	-	μs
Receiver Positive or Negative Threshold to INVALID High Delay (t <sub>INVH</sub> )			25	-	1	-	μs
Receiver Positive or $\frac{\text{Negative}}{\text{INVALID}} \text{ Low Delay } (t_{\text{INVL}})$				-	30	-	μs
RECEIVER INPUTS							
Input Voltage Range			25	-25	-	25	V
Input Threshold Low	$V_{CC} = 3.3V$		25	0.6	1.2	-	V
	V <sub>CC</sub> = 5.0V		25	0.8	1.5	-	V
Input Threshold High	$V_{CC} = 3.3V$		25	-	1.5	2.4	V
	V <sub>CC</sub> = 5.0V			-	1.8	2.4	V
Input Hysteresis			25	-	0.5	-	V
Input Resistance			25	3	5	7	kΩ
TRANSMITTER OUTPUTS				1 1		L	
Output Voltage Swing	All Transmitter Outputs L	oaded with $3k\Omega$ to Ground	Full	±5.0	±5.4	-	V
Output Resistance	$V_{CC} = V + = V - = 0V, T_{I}$	ransmitter Output = $\pm 2V$	Full	300	10M	-	Ω
Output Short-Circuit Current			Full	-	±35	±60	mA
Output Leakage Current	$V_{OUT} = \pm 12V$ , $V_{CC} = 0V$ or $3V$ to $5.5V$ , Automatic Power-Down or FORCEOFF = SHDN = GND			-	-	±25	μA
MOUSE DRIVEABILITY (	ICL324XE Only)						
Transmitter Output Voltage (see Figure 9)	$T1_{IN}$ = $T2_{IN}$ = GND, $T3_{IN}$ = $V_{CC}$ , $T3_{OUT}$ Loaded with 3k $\Omega$ to GND, $T1_{OUT}$ and $T2_{OUT}$ Loaded with 2.5mA Each			±5	-	-	V
TIMING CHARACTERISTI	CS						
Maximum Data Rate	$R_L = 3k\Omega$ , $C_L = 1000pR$ Switching	, One Transmitter	Full	250	500	-	kbps
Receiver Propagation Delay	Receiver Input to	t <sub>PHL</sub>	25	-	0.15	-	μs
	Receiver Output, $C_L = 150pF$	t <sub>PLH</sub>	25	-	0.15	-	μs
Receiver Output Enable Time	Normal Operation (Exce	ept ICL3232E)	25	-	200	-	ns

#### **Electrical Specifications**

Test Conditions:  $V_{CC}$  = 3V to 5.5V,  $C_1 - C_4 = 0.1 \mu$ F; Unless Otherwise Specified. Typicals are at  $T_A$  = +25°C. Boldface limits apply over the operating temperature range. (Continued)

PARAMETER	TEST CONDITIONS			MIN (Note 6)	ТҮР	MAX (Note 6)	UNITS
Receiver Output Disable Time	Normal Operation (Except ICL3232E)		25	-	200	-	ns
Transmitter Skew	t <sub>PHL</sub> to t <sub>PLH</sub> (Note 5)		25	-	100	-	ns
Receiver Skew	t <sub>PHL</sub> to t <sub>PLH</sub>		25	-	50	-	ns
Transition Region Slew Rate	$V_{CC} = 3.3V,$	$C_{L} = 150 pF to 2500 pF$	25	4	-	30	V/µs
	$ \begin{array}{c} R_L = 3 \mathrm{k} \Omega \text{ to } 7 \mathrm{k} \Omega, \\ \text{Measured from 3V to} \\ -3 \mathrm{V} \text{ or } -3 \mathrm{V} \text{ to 3V} \end{array}  \right. \\ \hline \\ \mathbf{C}_L = 150 \mathrm{pF} \text{ to } 1000 \mathrm{pF} \\ \end{array} $		25	6	-	30	V/µs
ESD PERFORMANCE	•					•	
RS-232 Pins (TOUT, RIN)	Human Body Model		25	-	±15	-	kV
	IEC61000-4-2 Contact Discharge		25	-	±8	-	kV
	IEC61000-4-2 Air Gap Discharge		25	-	±15	-	kV
All Other Pins	Human Body Model		25	-	±2	-	kV

NOTES:

5. Transmitter skew is measured at the transmitter zero crossing points.

6. Parameters with MIN and/or MAX limits are 100% tested at +25°C, unless otherwise specified. Temperature limits established by characterization and are not production tested.

### **Detailed Description**

ICL32xxE interface ICs operate from a single +3V to +5.5V supply, guarantee a 250kbps minimum data rate, require only four small external 0.1µF capacitors, feature low power consumption, and meet all EIA RS-232C and V.28 specifications. The circuit is divided into three sections: charge pump, transmitters and receivers.

#### Charge-Pump

Intersil's new ICL32xxE family utilizes regulated onchip dual charge pumps as voltage doublers, and voltage inverters to generate ±5.5V transmitter supplies from a V<sub>CC</sub> supply as low as 3.0V. This allows these devices to maintain RS-232 compliant output levels over the ±10% tolerance range of 3.3V powered systems. The efficient on-chip power supplies require only four small, external 0.1µF capacitors for the voltage doubler and inverter functions at V<sub>CC</sub> = 3.3V. See "Capacitor Selection" on page 18 and Table 3 on page 18 for capacitor recommendations for other operating conditions. The charge pumps operate discontinuously (i.e., they turn off as soon as the V+ and V- supplies are pumped up to the nominal values), resulting in significant power savings.

#### Transmitters

The transmitters are proprietary, low dropout, inverting drivers that translate TTL/CMOS inputs to EIA/TIA-232 output levels. Coupled with the on-chip  $\pm 5.5V$  supplies, these transmitters deliver true RS-232 levels over a wide range of single supply system voltages.

Except for the ICL3232E, all transmitter outputs disable and assume a high impedance state when the device enters the power-down mode (see Table 2). These outputs may be driven to  $\pm 12V$  when disabled.

All devices guarantee a 250kbps data rate for full load conditions (3k $\Omega$  and 1000pF),  $V_{CC} \geq 3.0V$ , with one transmitter operating at full speed. Under more typical conditions of  $V_{CC} \geq 3.3V$ ,  $R_L = 3k\Omega$ , and  $C_L = 250pF$ , one transmitter easily operates at 900kbps.

Transmitter inputs float if left unconnected, and may cause  ${\rm I}_{CC}$  increases. Connect unused inputs to GND for the best performance.

#### Receivers

All the ICL32xxE devices contain standard inverting receivers that three-state (except for the ICL3232E) via the EN or FORCEOFF control lines. Additionally, the two ICL324XE products include noninverting (monitor) receivers (denoted by the ROUTB label) that are always active, regardless of the state of any control lines. All the receivers convert RS-232 signals to CMOS output levels and accept inputs up to  $\pm 25V$  while presenting the required  $3k\Omega$  to  $7k\Omega$  input impedance (see Figure 1) even if the power is off (VCC = 0V). The receivers' Schmitt trigger input stage uses hysteresis to increase noise immunity and decrease errors due to slow input signal transitions.

The ICL3221E, ICL3222E, ICL3223E, <u>ICL3241E</u> inverting receivers disable only when EN is driven high. ICL3243E receivers disable during forced (manual) power-down, but not during automatic power-down (see Table 2). ICL3241E and ICL3243E monitor receivers remain active even during manual power-down and forced receiver disable, making them extremely useful for Ring Indicator monitoring. Standard receivers driving powered down peripherals must be disabled to prevent current flow through the peripheral's protection diodes (see Figures 2 and 3). This renders them useless for wake up functions, but the corresponding monitor receiver can be dedicated to this task as shown in Figure 3.





### **Low Power Operation**

These 3V devices require a nominal supply current of 0.3mA, even at  $V_{CC} = 5.5V$ , during normal operation (not in power-down mode). This is considerably less than the 5mA to 11mA current required by comparable 5V RS-232 devices, allowing users to reduce system power simply by switching to this new family.

# Pin Compatible Replacements for 5V Devices

The ICL3221E, ICL3222E, ICL3232E are pin compatible with existing 5V RS-232 transceivers - See the "Features" section on page 1 for details.

This pin compatibility coupled with the low  $I_{CC}$  and wide operating supply range, make the ICL32xxE potential lower power, higher performance drop-in replacements for existing 5V applications. As long as the  $\pm$ 5V RS-232 output swings are acceptable, and transmitter input pull-up resistors aren't required, the IICL32xxE should work in most 5V applications.

When replacing a device in an existing 5V application, it is acceptable to terminate  $C_3$  to  $V_{CC}$  as shown on the "Typical Operating Circuits" on page 2. Nevertheless, terminate  $C_3$  to GND if possible, as slightly better performance results from this configuration.

### Power-Down Functionality (Except ICL3232E)

The already low current requirement drops significantly when the device enters power-down mode. In power-down, supply current drops to 1 $\mu$ A, because the on-chip charge pump turns off (V+ collapses to V<sub>CC</sub>, V- collapses to GND), and the transmitter outputs three-state. Inverting receiver outputs may or may not disable in power-down; refer to Table 2 for details. This micro-power mode makes these devices ideal for battery powered and portable applications.

#### Software Controlled (Manual) Power-Down

Most devices in the ICL32xxE family provide pins that allow the user to force the IC into the low power, standby state.

On the ICL3222E and ICL3241E, the power-down control is via a simple shutdown (SHDN) pin. Driving this pin high enables normal operation, while driving it low forces the IC into its power-down state. Connect SHDN to  $V_{CC}$  if the power-down function isn't needed. Note that all the receiver outputs remain enabled during shutdown (see Table 2). For the lowest power consumption during power-down, the receivers should also be disabled by driving the EN input high (see next section, and Figures 2 and 3).

The ICL3221E, ICL3223E, and ICL3243E utilize a two pin approach where the FORCEON and FORCEOFF inputs determine the IC's mode. For always enabled operation, FORCEON and FORCEOFF are both strapped high. To switch between active and power-down modes, under logic or software control, only the FORCEOFF input need be driven. The FORCEON state isn't critical, as FORCEOFF dominates over FORCEON. Nevertheless, if strictly manual control over powerdown is desired, the user must strap FORCEON high to disable the automatic power-down circuitry. ICL3243E inverting (standard) receiver outputs also disable when the device is in manual power-down, thereby eliminating the possible current path through a shutdown peripheral's input protection diode (see Figures 2 and 3).

TABLE 2. POWER-DOWN AND ENABLE LOGIC TRUTH TABLE

RS-232 SIGNAL PRESENT AT RECEIVER INPUT?	FOR <u>CEOFF</u> OR SHDN INPUT	FORCEON INPUT	EN INPUT	TRANSMITTER OUTPUTS	RECEI VER OUTPUTS	Routb OUTPUTS (NOTE 7)	INVALID OUTPUT	MODE OF OPERATION
ICL3222E,	ICL3222E, ICL3241E							
N/A	L	N/A	L	High-Z	Active	Active	N/A	Manual Power-Down
N/A	L	N/A	Н	High-Z	High-Z	Active	N/A	Manual Power-Down with Receiver Disabled
N/A	Н	N/A	L	Active	Active	Active	N/A	Normal Operation
N/A	Н	N/A	Н	Active	High-Z	Active	N/A	Normal Operation with Receiver Disabled

15

RS-232 SIGNAL PRESENT AT RECEIVER INPUT?	FOR <u>CEOF</u> F OR SHDN INPUT	FORCEON INPUT	EN INPUT	TRANSMITTER OUTPUTS	RECEI VER OUTPUTS	Routb OUTPUTS (NOTE 7)	INVALID OUTPUT	MODE OF OPERATION
ICL3221E,	ICL3223E					•		
No	Н	Н	L	Active	Active	N/A	L	Normal Operation
No	Н	Н	Н	Active	High-Z	N/A	L	(Auto Power-Down Disabled)
Yes	Н	L	L	Active	Active	N/A	Н	Normal Operation
Yes	Н	L	Н	Active	High-Z	N/A	Н	(Auto Power-Down Enabled)
No	Н	L	L	High-Z	Active	N/A	L	Power-Down Due to Auto
No	Н	L	Н	High-Z	High-Z	N/A	L	Power-Down Logic
Yes	L	Х	L	High-Z	Active	N/A	Н	Manual Power-Down
Yes	L	Х	Н	High-Z	High-Z	N/A	Н	Manual Power-Down with Receiver Disabled
No	L	Х	L	High-Z	Active	N/A	L	Manual Power-Down
No	L	X	Н	High-Z	High-Z	N/A	L	Manual Power-Down with Receiver Disabled
ICL3243E								
No	Н	Н	N/A	Active	Active	Active	L	Normal Operation (Auto Power-Down Disabled)
Yes	Н	L	N/A	Active	Active	Active	Н	Normal Operation (Auto Power-Down Enabled)
No	Н	L	N/A	High-Z	Active	Active	L	Power-Down Due to Auto Power-Down Logic
Yes	L	Х	N/A	High-Z	High-Z	Active	Н	Manual Power-Down
No	L	Х	N/A	High-Z	High-Z	Active	L	Manual Power-Down

TABLE 2. POWER-DOWN AND ENABLE LOGIC TRUTH TABLE (Continued)

NOTE:

7. Applies only to the ICL3241E and ICL3243E.

The INVALID output always indicates whether or not a valid RS-232 signal is present at any of the receiver inputs (see Table 2), giving the user an easy way to determine when the interface block should power down. In the case of a disconnected interface cable where all the receiver inputs are floating (but pulled to GND by the internal receiver pull down resistors), the INVALID logic detects the invalid levels and drives the output low. The power management logic then uses this indicator to power down the interface block. Reconnecting the cable restores valid levels at the receiver inputs, **INVALID** switches high, and the power management logic wakes up the interface block. INVALID can also be used to indicate the DTR or RING INDICATOR signal, as long as the other receiver inputs are floating, or driven to GND (as in the case of a powered down driver). Connecting FORCEOFF and FORCEON together disables the automatic power-down feature, enabling them to function as a manual SHUTDOWN input (see Figure 4).





FIGURE 3. DISABLED RECEIVERS PREVENT POWER DRAIN





With any of the control schemes, the time required to exit power-down, and resume transmission is only 100µs. A mouse, or other application, may need more time to wake up from shutdown. If automatic power-down is being utilized, the RS-232 device will reenter power-down if valid receiver levels aren't reestablished within 30µs of the ICL32xxE powering up. Figure 5 illustrates a circuit that keeps the ICL32xxE from initiating automatic power-down for 100ms after powering up. This gives the slow-to-wake peripheral circuit time to reestablish valid RS-232 output levels.





#### Automatic Power-Down (ICL3221E, ICL3223E, ICL3243E Only)

Even greater power savings is available by using the devices which feature an *automatic* power-down function. When no valid RS-232 voltages (see Figure 6) are sensed on any receiver input for  $30\mu$ s, the charge pump and transmitters power-down, thereby reducing supply current to  $1\mu$ A. Invalid receiver levels occur whenever the driving peripheral's outputs are shut off (powered down) or when the RS-232 interface cable is disconnected. The ICL32xxE powers back up whenever it detects a valid RS-232 voltage level on any receiver input. This automatic power-down feature provides additional system power savings without changes to the existing operating system.





Automatic power-down operates when the FORCEON input is low, and the FORCEOFF input is high. Tying FORCEON high disables automatic power-down, but manual power-down is always available via the overriding FORCEOFF input. Table 2 summarizes the automatic power-down functionality.

Devices with the automatic power-down feature include an INVALID output signal, which switches low to indicate that invalid levels have persisted on all of the receiver inputs for more than  $30\mu s$  (see Figure 7). INVALID switches high  $1\mu s$  after detecting a valid RS-232 level on a receiver input. INVALID operates in all modes (forced or automatic power-down, or forced on), so it is also useful for systems employing manual power-down circuitry. When automatic power-down is utilized, INVALID = 0 indicates that the ICL32xxE is in power-down mode.

The time to recover from automatic power-down mode is typically  $100 \mu \text{s}.$ 



FIGURE 7. <u>AUTOMATIC POWER-DOWN AND</u> INVALID TIMING DIAGRAMS

#### Receiver ENABLE Control (ICL3221E, ICL3222E, ICL3223E, ICL3241E Only)

Several devices also feature an  $\overline{\text{EN}}$  input to control the receiver outputs. Driving  $\overline{\text{EN}}$  high disables all the inverting (standard) receiver outputs placing them in a high impedance state. This is useful to eliminate supply current, due to a receiver output forward biasing the protection diode, when driving the input of a powered down (V<sub>CC</sub> = GND) peripheral (see Figure 2). The enable input has no effect on transmitter nor monitor (R<sub>OUTB</sub>) outputs.

### **Capacitor Selection**

The charge pumps require  $0.1\mu$ F capacitors for 3.3V operation. For other supply voltages refer to Table 3 for capacitor values. Do not use values smaller than those listed in Table 3. Increasing the capacitor values (by a factor of 2) reduces ripple on the transmitter outputs and slightly reduces power consumption. C<sub>2</sub>, C<sub>3</sub>, and C<sub>4</sub> can be increased without increasing C<sub>1</sub>'s value, however, do not increase C<sub>1</sub> without also increasing C<sub>2</sub>, C<sub>3</sub>, and C<sub>4</sub> to maintain the proper ratios (C<sub>1</sub> to the other capacitors).

When using minimum required capacitor values, make sure that capacitor values do not degrade excessively with temperature. If in doubt, use capacitors with a larger nominal value. The capacitor's equivalent series resistance (ESR) usually rises at low temperatures and it influences the amount of ripple on V+ and V-.

TABLE 3. REQUIRED CAPACITOR VALUES
------------------------------------

V <sub>CC</sub> (V)	С <sub>1</sub> (µF)	C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> (µF)
3.0 to 3.6	0.1	0.1
4.5 to 5.5	0.047	0.33
3.0 to 5.5	0.1	0.47

### **Power Supply Decoupling**

In most circumstances a  $0.1\mu\text{F}$  bypass capacitor is adequate. In applications that are particularly sensitive to power supply noise, decouple  $V_{CC}$  to ground with a capacitor of the same value as the charge-pump capacitor  $C_1$ . Connect the bypass capacitor as close as possible to the IC.

### **Operation Down to 2.7V**

ICL32xxE transmitter outputs meet RS-562 levels (±3.7V), at full data rate, with V<sub>CC</sub> as low as 2.7V. RS-562 levels typically ensure interoperability with RS-232 devices.

### Transmitter Outputs when Exiting Power-Down

Figure 8 shows the response of two transmitter outputs when exiting power-down mode. As they activate, the two transmitter outputs properly go to opposite RS-232 levels, with no glitching, ringing, nor undesirable transients. Each transmitter is loaded with  $3k\Omega$  in parallel with 2500pF. Note that the transmitters enable only when the magnitude of the supplies exceed approximately 3V.



FIGURE 8. TRANSMITTER OUTPUTS WHEN EXITING POWER-DOWN

### Mouse Driveability

The ICL3241E and ICL3243E have been specifically designed to power a serial mouse while operating from low voltage supplies. Figure 9 shows the transmitter

output voltages under increasing load current. The on-chip switching regulator ensures the transmitters will supply at least  $\pm$ 5V during worst case conditions (15mA for paralleled V+ transmitters, 7.3mA for single V-transmitter). The Automatic Power-Down feature does not work with a mouse, so FORCEOFF and FORCEON should be connected to V<sub>CC</sub>.



### **High Data Rates**

The ICL32xxE maintain the RS-232  $\pm$ 5V minimum transmitter output voltages even at high data rates. Figure 10 details a transmitter loopback test circuit, and Figure 11 illustrates the loopback test result at 120kbps. For this test, all transmitters were simultaneously driving RS-232 loads in parallel with 1000pF, at 120kbps. Figure 12 shows the loopback results for a single transmitter driving 1000pF and an RS-232 load at 250kbps. The static transmitters were also loaded with an RS-232 receiver.



FIGURE 10. TRANSMITTER LOOPBACK TEST CIRCUIT



FIGURE 11. LOOPBACK TEST AT 120kbps



FIGURE 12. LOOPBACK TEST AT 250kbps

# Interconnection with 3V and 5V Logic

The ICL32XX directly interface with 5V CMOS and TTL logic families. Nevertheless, with the ICL32XX at 3.3V, and the logic supply at 5V, AC, HC, and CD4000 outputs can drive ICL32XX inputs, but ICL32XX outputs do not reach the minimum  $V_{IH}$  for these logic families. See Table 4 for more information.

TABLE 4. LOGIC FAMILY C	OMPATIBILITY WITH
VARIOUS SUPPL	Y VOLTAGES

SYSTEM POWER-SUPPLY VOLTAGE (V)	V <sub>CC</sub> SUPPLY VOLTAGE (V)	COMPATIBILITY
3.3	3.3	Compatible with all CMOS families.
5	5	Compatible with all TTL and CMOS logic families.

#### TABLE 4. LOGIC FAMILY COMPATIBILITY WITH VARIOUS SUPPLY VOLTAGES (Continued)

SYSTEM POWER-SUPPLY VOLTAGE (V)	V <sub>CC</sub> SUPPLY VOLTAGE (V)	COMPATIBILITY
5	3.3	Compatible with ACT and HCT CMOS, and with TTL. ICL32XX outputs are incompatible with AC, HC, and CD4000 CMOS inputs.

### ±15kV ESD Protection

All pins on ICL32XX devices include ESD protection structures, but the ICL32xxE family incorporates advanced structures which allow the RS-232 pins (transmitter outputs and receiver inputs) to survive ESD events up to  $\pm 15$ kV. The RS-232 pins are particularly vulnerable to ESD damage because they typically connect to an exposed port on the exterior of the finished product. Simply touching the port pins, or connecting a cable, can cause an ESD event that might destroy unprotected ICs. These new ESD structures protect the device whether or not it is powered up, protect without allowing any latch-up mechanism to activate, and don't interfere with RS-232 signals as large as  $\pm 25$ V.

#### Human Body Model (HBM) Testing

As the name implies, this test method emulates the ESD event delivered to an IC during human handling. The tester delivers the charge through a  $1.5k\Omega$  current limiting resistor, making the test less severe than the IEC61000 test which utilizes a  $330\Omega$  limiting resistor. The HBM method determines an IC's ability to withstand the ESD transients typically present during handling and manufacturing. Due to the random nature of these events, each pin is tested with respect to all other pins. The RS-232 pins on "E" family devices can withstand HBM ESD events to  $\pm 15kV$ .

#### IEC61000-4-2 Testing

The IEC61000 test method applies to finished equipment, rather than to an individual IC. Therefore, the pins most likely to suffer an ESD event are those that are exposed to the outside world (the RS-232 pins in this case), and the IC is tested in its typical application configuration (power applied) rather than testing each pin-to-pin combination. The lower current limiting resistor coupled with the larger charge storage capacitor yields a test that is much more severe than the HBM test. The extra ESD protection built into this device's RS-232 pins allows the design of equipment meeting level 4 criteria without the need for additional board level protection on the RS-232 port.

#### AIR-GAP DISCHARGE TEST METHOD

For this test method, a charged probe tip moves toward the IC pin until the voltage arcs to it. The current waveform delivered to the IC pin depends on approach speed, humidity, temperature, etc., so it is difficult to obtain repeatable results. The "E" device RS-232 pins withstand  $\pm 15$ kV air-gap discharges.

#### CONTACT DISCHARGE TEST METHOD

During the contact discharge test, the probe contacts the tested pin before the probe tip is energized, thereby eliminating the variables associated with the air-gap discharge. The result is a more repeatable and predictable test, but equipment limits prevent testing devices at voltages higher than  $\pm 8$ kV. All "E" family devices survive  $\pm 8$ kV contact discharges on the RS-232 pins.

### **Typical Performance Curves** $v_{CC} = 3.3V$ , $T_A = +25$ °C.









### **Typical Performance Curves** $V_{CC} = 3.3V$ , $T_A = +25^{\circ}C$ . (Continued)









### **Die Characteristics**

SUBSTRATE POTENTIAL (POWERED UP):

GND

#### TRANSISTOR COUNT:

ICL3221E: 286 ICL3222E: 338 ICL3223E: 357 ICL3232E: 296 ICL324XE: 464

PROCESS:

Si Gate CMOS







FIGURE 18. SUPPLY CURRENT vs SUPPLY VOLTAGE

### **Revision History**

The revision history provided is for informational purposes only and is believed to be accurate, but not warranted. Please go to web to make sure you have the latest Rev.

DATE	REVISION	CHANGE
2/22/10	FN4910.21	Revision history begins with this revision.
		Converted to new Intersil template.
		Added new temp grade ( $F$ = extended industrial) to ICL3232. Updated ordering info table, Operating Conditions, and added 125°C specs for input lkg currents, and rcvr output high voltage.
		Pages 8-10: Removed all withdrawn devices from Ordering Information table.
		Pages 12-14: Added "Boldface limits apply over the operating temperature range." to common conditions of Electrical Specs table. Replaced Note 6 "Parts are 100% tested at +25°C. Full temp limits are guaranteed by bench and tester characterization." with "Parameters with MIN and/or MAX limits are 100% tested at +25°C, unless otherwise specified. Temperature limits established by characterization and are not production tested."

### Products

Intersil Corporation is a leader in the design and manufacture of high-performance analog semiconductors. The Company's products address some of the industry's fastest growing markets, such as, flat panel displays, cell phones, handheld products, and notebooks. Intersil's product families address power management and analog signal processing functions. Go to <u>www.intersil.com/products</u> for a complete list of Intersil product families.

\*For a complete listing of Applications, Related Documentation and Related Parts, please see the respective device information page on intersil.com: ICL3221E, ICL3222E, ICL3223E, ICL3232E, ICL3241E, ICL3243E

To report errors or suggestions for this datasheet, please go to www.intersil.com/askourstaff

FITs are available from our website at <a href="http://rel.intersil.com/reports/search.php">http://rel.intersil.com/reports/search.php</a>

### Dual-In-Line Plastic Packages (PDIP)



#### NOTES:

- 1. Controlling Dimensions: INCH. In case of conflict between English and Metric dimensions, the inch dimensions control.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- 3. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication No. 95.
- 4. Dimensions A, A1 and L are measured with the package seated in JEDEC seating plane gauge GS-3.
- 5. D, D1, and E1 dimensions do not include mold flash or protrusions. Mold flash or protrusions shall not exceed 0.010 inch (0.25mm).
- E and e<sub>A</sub> are measured with the leads constrained to be perpendicular to datum -C-.
- 7.  $e_B$  and  $e_C$  are measured at the lead tips with the leads unconstrained.  $e_C$  must be zero or greater.
- 8. B1 maximum dimensions do not include dambar protrusions. Dambar protrusions shall not exceed 0.010 inch (0.25mm).
- 9. N is the maximum number of terminal positions.
- Corner leads (1, N, N/2 and N/2 + 1) for E8.3, E16.3, E18.3, E28.3 may have a B1 dimension of 0.030 - 0.045 inch (0.76 - 1.14mm).

#### E18.3 (JEDEC MS-001-BC ISSUE D) 18 LEAD DUAL-IN-LINE PLASTIC PACKAGE

	INC	HES	MILLIN	IETERS	
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	-	0.210	-	5.33	4
A1	0.015	-	0.39	-	4
A2	0.115	0.195	2.93	4.95	-
В	0.014	0.022	0.356	0.558	-
B1	0.045	0.070	1.15	1.77	8, 10
С	0.008	0.014	0.204	0.355	-
D	0.845	0.880	21.47	22.35	5
D1	0.005	-	0.13	-	5
Е	0.300	0.325	7.62	8.25	6
E1	0.240	0.280	6.10	7.11	5
е	0.100	BSC	2.54	BSC	-
e <sub>A</sub>	0.300	BSC	7.62	7.62 BSC	
е <sub>В</sub>	-	0.430	-	10.92	7
L	0.115	0.150	2.93	3.81	4
Ν	1	8	1	8	9

Rev. 2 11/03

#### Small Outline Plastic Packages (SOIC)



NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- 4. Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.25mm (0.010 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. The lead width "B", as measured 0.36mm (0.014 inch) or greater above the seating plane, shall not exceed a maximum value of 0.61mm (0.024 inch).
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M16.15 (JEDEC MS-012-AC ISSUE C) 16 LEAD NARROW BODY SMALL OUTLINE PLASTIC PACKAGE

	INCHES		MILLIMETERS		
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	0.0532	0.0688	1.35	1.75	-
A1	0.0040	0.0098	0.10	0.25	-
В	0.013	0.020	0.33	0.51	9
С	0.0075	0.0098	0.19	0.25	-
D	0.3859	0.3937	9.80	10.00	3
Е	0.1497	0.1574	3.80	4.00	4
е	0.050	BSC	1.27 BSC		-
Н	0.2284	0.2440	5.80	6.20	-
h	0.0099	0.0196	0.25	0.50	5
L	0.016	0.050	0.40	1.27	6
Ν	1	16		16	7
α	0°	8°	0°	8°	-

### Thin Shrink Small Outline Plastic Packages (TSSOP)



#### NOTES:

- 1. These package dimensions are within allowable dimensions of JEDEC MO-153-AB, Issue E.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- Dimension "E1" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.15mm (0.006 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- Dimension "b" does not include dambar protrusion. Allowable dambar protrusion shall be 0.08mm (0.003 inch) total in excess of "b" dimension at maximum material condition. Minimum space between protrusion and adjacent lead is 0.07mm (0.0027 inch).
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact. (Angles in degrees)

#### M16.173

#### 16 LEAD THIN SHRINK SMALL OUTLINE PLASTIC PACKAGE

	INC	HES	MILLIMETERS		
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	-	0.043	-	1.10	-
A1	0.002	0.006	0.05	0.15	-
A2	0.033	0.037	0.85	0.95	-
b	0.0075	0.012	0.19	0.30	9
С	0.0035	0.008	0.09	0.20	-
D	0.193	0.201	4.90	5.10	3
E1	0.169	0.177	4.30	4.50	4
е	0.026	BSC	0.65 BSC		-
Е	0.246	0.256	6.25	6.50	-
L	0.020	0.028	0.50	0.70	6
Ν	1	16		6	7
α	0 <sup>0</sup>	8 <sup>0</sup>	0 <sup>0</sup>	8 <sup>0</sup>	-

Rev. 1 2/02

#### Small Outline Plastic Packages (SSOP)



#### NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.20mm (0.0078 inch) per side.
- Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.20mm (0.0078 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- Dimension "B" does not include dambar protrusion. Allowable dambar protrusion shall be 0.13mm (0.005 inch) total in excess of "B" dimension at maximum material condition.
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M16.209 (JEDEC MO-150-AC ISSUE B) 16 LEAD SHRINK SMALL OUTLINE PLASTIC PACKAGE

	INC	INCHES		MILLIMETERS		
SYMBOL	MIN	MAX	MIN	MAX	NOTES	
А	-	0.078	-	2.00	-	
A1	0.002	-	0.05	-	-	
A2	0.065	0.072	1.65	1.85	-	
В	0.009	0.014	0.22	0.38	9	
С	0.004	0.009	0.09	0.25	-	
D	0.233	0.255	5.90	6.50	3	
E	0.197	0.220	5.00	5.60	4	
е	0.026	BSC	0.65 BSC		-	
Н	0.292	0.322	7.40	8.20	-	
L	0.022	0.037	0.55	0.95	6	
Ν	1	6	1	6	7	
α	0°	8°	0°	8°	-	
				-	0 0/07	

Rev. 3 6/05

### Small Outline Plastic Packages (SOIC)



NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- 4. Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.25mm (0.010 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. The lead width "B", as measured 0.36mm (0.014 inch) or greater above the seating plane, shall not exceed a maximum value of 0.61mm (0.024 inch)
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M16.3 (JEDEC MS-013-AA ISSUE C) 16 LEAD WIDE BODY SMALL OUTLINE PLASTIC PACKAGE

	INCHES MILLIMETERS		<b>METERS</b>		
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	0.0926	0.1043	2.35	2.65	-
A1	0.0040	0.0118	0.10	0.30	-
В	0.013	0.0200	0.33	0.51	9
С	0.0091	0.0125	0.23	0.32	-
D	0.3977	0.4133	10.10	10.50	3
E	0.2914	0.2992	7.40	7.60	4
е	0.050	BSC	1.27 BSC		-
Н	0.394	0.419	10.00	10.65	-
h	0.010	0.029	0.25	0.75	5
L	0.016	0.050	0.40	1.27	6
Ν	16			16	7
α	0°	8°	0°	8°	-

### Small Outline Plastic Packages (SOIC)



#### NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- 4. Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.25mm (0.010 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. The lead width "B", as measured 0.36mm (0.014 inch) or greater above the seating plane, shall not exceed a maximum value of 0.61mm (0.024 inch)
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M18.3 (JEDEC MS-013-AB ISSUE C) 18 LEAD WIDE BODY SMALL OUTLINE PLASTIC PACKAGE

	INC	HES	MILLIN	MILLIMETERS	
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	0.0926	0.1043	2.35	2.65	-
A1	0.0040	0.0118	0.10	0.30	-
В	0.013	0.0200	0.33	0.51	9
С	0.0091	0.0125	0.23	0.32	-
D	0.4469	0.4625	11.35	11.75	3
Е	0.2914	0.2992	7.40	7.60	4
е	0.050	BSC	1.27 BSC		-
Н	0.394	0.419	10.00	10.65	-
h	0.010	0.029	0.25	0.75	5
L	0.016	0.050	0.40	1.27	6
Ν	1	18		18	7
α	0°	8°	0°	8°	-

### Thin Shrink Small Outline Plastic Packages (TSSOP)



#### NOTES:

- 1. These package dimensions are within allowable dimensions of JEDEC MO-153-AC, Issue E.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- 4. Dimension "E1" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.15mm (0.006 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. Dimension "b" does not include dambar protrusion. Allowable dambar protrusion shall be 0.08mm (0.003 inch) total in excess of "b" dimension at maximum material condition. Minimum space between protrusion and adjacent lead is 0.07mm (0.0027 inch).
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact. (Angles in degrees)

#### M20.173

20 LEAD THIN SHRINK SMALL OUTLINE PLASTIC PACKAGE

	INCHES MILLIMETERS				
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	-	0.047	-	1.20	-
A1	0.002	0.006	0.05	0.15	-
A2	0.031	0.051	0.80	1.05	-
b	0.0075	0.0118	0.19	0.30	9
С	0.0035	0.0079	0.09	0.20	-
D	0.252	0.260	6.40	6.60	3
E1	0.169	0.177	4.30	4.50	4
е	0.026	BSC	0.65 BSC		-
E	0.246	0.256	6.25	6.50	-
L	0.0177	0.0295	0.45	0.75	6
Ν	20		2	20	7
α	0 <sup>0</sup>	8 <sup>0</sup>	0 <sup>0</sup>	8 <sup>0</sup>	-

#### Shrink Small Outline Plastic Packages (SSOP)



#### NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.20mm (0.0078 inch) per side.
- 4. Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.20mm (0.0078 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. Dimension "B" does not include dambar protrusion. Allowable dambar protrusion shall be 0.13mm (0.005 inch) total in excess of "B" dimension at maximum material condition.
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M20.209 (JEDEC MO-150-AE ISSUE B) 20 LEAD SHRINK SMALL OUTLINE PLASTIC PACKAGE

i							
	INC	HES	MILLIMETERS				
SYMBOL	MIN	MAX	MIN	MAX	NOTES		
А	0.068	0.078	1.73	1.99			
A1	0.002	0.008'	0.05	0.21			
A2	0.066	0.070'	1.68	1.78			
В	0.010'	0.015	0.25	0.38	9		
С	0.004	0.008	0.09	0.20'			
D	0.278	0.289	7.07	7.33	3		
E	0.205	0.212	5.20'	5.38	4		
е	0.026	BSC	0.65 BSC				
Н	0.301	0.311	7.65	7.90'			
L	0.025	0.037	0.63	0.95	6		
N	2	0	2	0	7		
α	0 deg.	8 deg.	0 deg.	8 deg.			

Rev. 3 11/02

### Thin Shrink Small Outline Plastic Packages (TSSOP)



#### NOTES:

- 1. These package dimensions are within allowable dimensions of JEDEC MO-153-AE, Issue E.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- 4. Dimension "E1" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.15mm (0.006 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. Dimension "b" does not include dambar protrusion. Allowable dambar protrusion shall be 0.08mm (0.003 inch) total in excess of "b" dimension at maximum material condition. Minimum space between protrusion and adjacent lead is 0.07mm (0.0027 inch).
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact. (Angles in degrees)

#### M28.173

28 LEAD THIN SHRINK SMALL OUTLINE PLASTIC PACKAGE

	INCHES		MILLIMETERS		
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	-	0.047	-	1.20	-
A1	0.002	0.006	0.05	0.15	-
A2	0.031	0.051	0.80	1.05	-
b	0.0075	0.0118	0.19	0.30	9
с	0.0035	0.0079	0.09	0.20	-
D	0.378	0.386	9.60	9.80	3
E1	0.169	0.177	4.30	4.50	4
е	0.026	BSC	0.65 BSC		-
E	0.246	0.256	6.25	6.50	-
L	0.0177	0.0295	0.45	0.75	6
Ν	2	28		28	7
α	0 <sup>0</sup>	8 <sup>0</sup>	0 <sup>0</sup>	8 <sup>0</sup>	-

Rev. 0 6/98

#### Shrink Small Outline Plastic Packages (SSOP)



#### NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.20mm (0.0078 inch) per side.
- 4. Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.20mm (0.0078 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. Dimension "B" does not include dambar protrusion. Allowable dambar protrusion shall be 0.13mm (0.005 inch) total in excess of "B" dimension at maximum material condition.
- 10. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M28.209 (JEDEC MO-150-AH ISSUE B) 28 LEAD SHRINK SMALL OUTLINE PLASTIC PACKAGE

	INC	INCHES		MILLIMETERS		
SYMBOL	MIN	MAX	MIN	MAX	NOTES	
А	-	0.078	-	2.00	-	
A1	0.002	-	0.05	-	-	
A2	0.065	0.072	1.65	1.85	-	
В	0.009	0.014	0.22	0.38	9	
С	0.004	0.009	0.09	0.25	-	
D	0.390	0.413	9.90	10.50	3	
E	0.197	0.220	5.00	5.60	4	
е	0.026	BSC	0.65 BSC		-	
Н	0.292	0.322	7.40	8.20	-	
L	0.022	0.037	0.55	0.95	6	
Ν	2	8	2	28	7	
α	0°	8°	0°	8°	-	

Rev. 2 6/05

#### Small Outline Plastic Packages (SOIC)



#### NOTES:

- 1. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication Number 95.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- Dimension "D" does not include mold flash, protrusions or gate burrs. Mold flash, protrusion and gate burrs shall not exceed 0.15mm (0.006 inch) per side.
- 4. Dimension "E" does not include interlead flash or protrusions. Interlead flash and protrusions shall not exceed 0.25mm (0.010 inch) per side.
- 5. The chamfer on the body is optional. If it is not present, a visual index feature must be located within the crosshatched area.
- 6. "L" is the length of terminal for soldering to a substrate.
- 7. "N" is the number of terminal positions.
- 8. Terminal numbers are shown for reference only.
- 9. The lead width "B", as measured 0.36mm (0.014 inch) or greater above the seating plane, shall not exceed a maximum value of 0.61mm (0.024 inch)
- Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.

#### M28.3 (JEDEC MS-013-AE ISSUE C) 28 LEAD WIDE BODY SMALL OUTLINE PLASTIC PACKAGE

	INC	HES	MILLIN	<b>METERS</b>	
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	0.0926	0.1043	2.35	2.65	-
A1	0.0040	0.0118	0.10	0.30	-
В	0.013	0.0200	0.33	0.51	9
С	0.0091	0.0125	0.23	0.32	-
D	0.6969	0.7125	17.70	18.10	3
Е	0.2914	0.2992	7.40	7.60	4
е	0.05	BSC	1.27 BSC		-
Н	0.394	0.419	10.00	10.65	-
h	0.01	0.029	0.25	0.75	5
L	0.016	0.050	0.40	1.27	6
Ν	2	8	:	28	7
α	0 <sup>0</sup>	8 <sup>0</sup>	0 <sup>0</sup>	8 <sup>0</sup>	-

Rev. 0 12/93

For additional products, see www.intersil.com/product\_tree

Intersil products are manufactured, assembled and tested utilizing ISO9000 quality systems as noted in the quality certifications found at <u>www.intersil.com/design/quality</u>

Intersil products are sold by description only. Intersil Corporation reserves the right to make changes in circuit design, software and/or specifications at any time without notice. Accordingly, the reader is cautioned to verify that data sheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.

For information regarding Intersil Corporation and its products, see www.intersil.com

